

PORTABLE SINGLE-PHASE POWER GENERATOR /
OUTPUT POWER **7 KVA** SINGLE-PHASE /
PETROL ENGINE **3000 RPM**

Gen Set Features	<ul style="list-style-type: none"> + Low oil level cut out device + 1 x 32A, 230 V - 50 Hz single-phase EEC socket protected by circuit breaker + 1 x 16A, 230 V - 50 Hz single-phase EEC socket protected by circuit breaker + 1 x 12V DC battery charger outlet protected by fuse + Earth Leakage Circuit Breaker (ELCB)
Gen Set Options (available as factory options)	+ Not available
Accessories on Request	+ Trolley: two-wheels and handles
Noise Level	+ LWA 97 (72 dB at 7m)
AC Generator 50 Hz	<ul style="list-style-type: none"> + Type synchronous + Single-phase power (max.) 7 kVA - 230 V + Battery Charger 120 W - 12 V - 10 A - CC + Power Factor 0,8
Petrol Engine 3000 rpm	<ul style="list-style-type: none"> + Type Honda GX 390 OHV - 1 cyl. - 13 HP (9,6 kWm) - 390 cm³ + Fuel petrol + Cooling system air + Starting system manual recoil + Fuel tank capacity 6,5 l + Fuel consumption @ 75% 2,9 l/h
Other Features	<ul style="list-style-type: none"> + Insulation Class H + Mechanical Protection IP 23 + Dimensions (L x W x H) 730 x 480 x 520 mm + Dry Weight 80 kg

EA 80 GH

